

Inverted LED Display

```
<sxh [py]; options for SyntaxHighlighter> #!/usr/bin/python # Python Script to run a 7 Segment Common Anode LED as a clock. #
Version 1.0 import RPi.GPIO as GPIO import time
```

```
#Define numbering system for the IO pins Raspberry Pi GPIO.setmode(GPIO.BCM)
```

```
# Define GPIO ports for the 7seg gpioSegments = (5,6,13,19,26,21,20,16) # 7seg_segment_pins (11,7,4,2,1,10,5,3) + 100R inline # Setup
channels for output and set initial values for segment in (gpioSegments):
```

```
GPIO.setup(segment,GPIO.OUT)
GPIO.output(segment,GPIO.HIGH)
```

```
# Define GPIO ports for the digits 0-3 gpioDigits = (18,23,24,25) gpioDigits = (25,24,23,18) # Pins (12,9,8,6) select digits 0-3 respectively
reading LTR on display # Setup channels for output and set initial values for digit in (gpioDigits):
```

```
GPIO.setup(digit,GPIO.OUT)
GPIO.output(digit,GPIO.LOW)
```

```
#Define flags for control of Colon separator on display colon_visible=True colon_counter=0
```

```
#Define segment arrays for each number to be displayed numbers = {
```

```
'0':(0,0,1,0,1,0,0,0),
'1':(0,1,1,1,1,1,0,1),
'2':(0,0,1,1,0,0,1,0),
'3':(0,0,1,1,0,1,0,0),
'4':(0,1,1,0,0,1,0,1),
'5':(1,0,1,0,0,1,0,0),
'6':(1,0,1,0,0,0,0,0),
'7':(0,0,1,1,1,1,0,1),
'8':(0,0,1,0,0,0,0,0),
'9':(0,0,1,0,0,1,0,0),
' ': (0,0,0,0,0,0,0,0)}
```

```
#Cycle through each digit and its segments try:
```

```
while True:
    time_string = str(time.ctime()[11:13]+time.ctime()[14:16]).rjust(4)
    for digit in range(4):
```

```
#select digit to display
```

```
GPIO.output(gpioDigits[digit], 2)
```

```
#set required segments on
```

```
for segment in range(0,8):
    GPIO.output(gpioSegments[segment], numbers[time_string[digit]][segment])
```

```
#check to see if we are on segment 3 of digit 2(LTR)
```

```
if ((digit==2) and (segment==2)):
```

```
#when colon counter gets to set value flip colon display mode between TRUE (visible) and False (NOT.visible)
```

```
if (colon_counter<=25):
```

```
#count value not reached turn colon ON or OFF based on current setting of colon_visible
```

```
if colon_visible==True:
    GPIO.output(13, 0)
else:
    GPIO.output(13, 1)
```

```
#colon counter set value reached so flip colon display mode and reset colon counter
```

```
        else:
            colon_counter = 0
            colon_visible = not colon_visible
```

#display all selected segments for a short time

```
        time.sleep(0.005)
```

#turn-off All segments

```
        for segment in range(0,8):
            GPIO.output(gpioSegments[segment],GPIO.HIGH)
```

#turn-off current digit selector pin

```
        GPIO.output(gpioDigits[digit], GPIO.LOW)
```

#advance colon counter

```
        colon_counter=colon_counter+1
```

finally:

```
GPIO.cleanup()
```

</sxh>

From:

<https://wiki.alanwalker.uk/> - WalkerWiki - wiki.alanwalker.uk

Permanent link:

https://wiki.alanwalker.uk/doku.php?id=inverted_led_display&rev=1491340281

Last update: **2023/03/09 22:35**

